



85241179



IP20

## Blind button Berker K.1, polar white glossy

Technical features

#### **Functions**

Venetian blind movement time 2 mn

- Memory function for automatic execution of learned up and down times with position
- Party function, no execution of automatic, radio and extension unit commands (lock-out protection)

## **Controls and indicators**

- activation of the party function using buttons in up and down direction > 20 sec.

#### Main electrical features

| Nominal voltage | 12 V |
|-----------------|------|
| Frequency       | - Hz |

## Measurement

Relative humidity (without condensation) 0...65 % (without condensation)

#### Detection

- Not suitable for rain and wind sensors

## Materials

| Colour of design line | polar white   |
|-----------------------|---------------|
| Colour                | polarwhite    |
| Material              | thermoplastic |

## **LED** control

| LED | LED application module/insert compatibility display, |
|-----|--|
|     | with status LED for memory and party function,       |
|     | red/orange, with indicator LED for lock-out          |
|     | protection   |

## Installation, mounting

| Installation mode | clamp fastening |
|-------------------|-----------------|
|                   |                 |

# Settings

| Lamella adjusting time             | (adjustable) 50 ms2,5 s |
|------------------------------------|-------------------------|
| Minimum slat adjustment time       | ≈ 250 ms                |
| Delay time, adjustable             | 0500 s                  |
| Lamella adjustment on button-press | < 0,4 s                 |
|                                    |                         |

## Equipment

| Self-retaining for 2 min on button-press | > 0,4 s |
|--|---------|
| Change-over time for change of direction | < 0,6 s |

## Safety

- with dismantling protection



# Use conditions

| Operating temperature                                   | -545 °C                          |
|---|----------------------------------|
| - low intrinsic energy requirement                      |                                  |
| Identification  |                                  |
| Application, usage                                      | Blind control                    |
| Main design line  | Berker K.1                       |
| Secondary design line(s)                                | Electronics platform, Berker K.1 |
| Instructions  |                                  |
| - Can be switched to orientation led by extension unit. |                                  |