		Blind time switch Berker Q.1/Q.3/Q.7/Q.9, polar white v	<i>v</i> elvety
	$\bigtriangleup$		
		Technical features	
		Functions	
		Venetian blind movement time	2 mn
		- Memory function for automatic execution of learned	
	$\bigtriangledown$	- Party function, no execution of automatic, radio and e	extension unit commands (lock-out protection)
		Controls and indicators	
85241129		<ul> <li>activation of the party function using buttons in up ar</li> </ul>	nd down direction > 20 sec
$\sum_{i=1}^{n}$			
$\overline{\mathbf{v}}$		Main electrical features	
IP20		Nominal voltage	12 V
		Frequency	- Hz
		Measurement	
		Relative humidity (without condensation)	065 % (without condensation)
		Detection	
		- Not suitable for rain and wind sensors	
		Materials	
		Colour of design line	polar white
		Colour	polarwhite
		Material	thermoplastic
		LED control	
		LED I	LED application module/insert compatibility display, with status LED for memory and party function, red/orange, with indicator LED for lock-out protection
		Installation, mounting	
		Installation mode	clamp fastening
		Settings	
		Lamella adjusting time	(adjustable) 50 ms2,5 s
		Minimum slat adjustment time	≈ 250 ms
		Delay time, adjustable	0500 s
		Lamella adjustment on button-press	< 0,4 s
		Equipment	
		Self-retaining for 2 min on button-press	> 0,4 s
		Change-over time for change of direction	< 0,6 s
		Safety	
		- with dismantling protection	



## Use conditions

-545 °C

Application, usage	Blind control
Main design line	Berker Q.1/Q.3/Q.7/Q.9
Secondary design line(s)	Berker Q.1, Berker Q.3, Berker Q.7, Berker Q.9

## Instructions

- Can be switched to orientation led by extension unit.